Malfunction Analysis and Troubleshooting

| Malfunction | Analysis | Troubleshooting |
|---|---|---|
| All indicator lights in red or no light, unable to start. | Ran out of battery. | Charge it for 3 to 5 hours to make sure that it gets a full charge. |
| All indicator lights flicker in red and green alternately, unable to start. | The jar is not tighten to the base. | Tighten the jar and base, make sure the magnet is aligned with the power button. |
| Stop working, all indicator lights flicker in red for 8 seconds. | Ingredient is too thick or volume too big, motor overload protection. | Add some liquid or cut ingredients into smaller pieces or shift into Pulse Mode, then restart it. |
| Leakage. | The seal is not placed properly; jar/cap is cross-threaded. | Check seals; check thread alignment when screwing on jar/cap. |

Like & Follow On: Facebook.com/ **BottleRocketBlenders**

NOTE:

- Product is suitable for USB Type-C cable. Suitable for power bank charging as well
- . When not used for a long time, charge it fully to keep battery in high voltage state in order to prevent damage.

Shop, Share & Review On: Amazon.com/Shops/ **Bottlerocketblenders**



it in the









Food Contact

BUTTLE ROCKET

Handy loop

Cap Button

Cautions

- DO NOT remove the lid or add in something rigid in your blender when it is
- DO NOT submerge the base into water to prevent base elements from damaging and make sure it is off before cleaning.
- DO NOT disinfect your blender in microwave or hot water above 80°C.
- DO NOT put your blender in freezer.
- . DO NOT clean your blender with any kind of metallic spiral ball to prevent parts from scratching or damaging.
- DO NOT clean your blender with a dishwasher machine.
- . DO NOT charge your blender when it is wet.
- DO NOT repair or disassemble it by yourself otherwise your warranty will be void. If malfunction occurred, kindly contact us

The USB-C port is waterproof, but do not soak the base in water or put it into the dishwasher for cleaning. This will damage the unit and VOID the Warranty!



PORTABLE BLENDER Imported Environmental-friendly Materials CE, ROHS, FCC Approval



Step 1

Cut fruits into small pieces before adding into the blender to fill up about 60% of the



Tighten the lid and tilt down the blender to make sure fruit pieces are not stuck under

!!!WARNING!!! KEEP OUT OF **REACH OF CHILDREN**



Step 2

Add some drinkable liquid until it reaches



power button to start blending and green lights flashing. Slightly tilt it back and forth while blending if desired Click once again to pause.

Pulse Mode: Doubleclick power button to enter into pulse mode While vellow lights flicker, press and hold the power button repeatedly to pulse.Pulse mode will

automatically end after

5S of inactivity and

Blend Mode: Click once Check Battery Level (The last second of LED light color displays battery capacity under Blend Mode) 1%- 17%: no lights 18%-33%: 2 green lights on

Food Grade AS Jar

6-Points Stainless Stee

Power Button

Charging Port

Typc-C

34%-50% . 4 green lights on 51%-67%: 6 green lights on 68%-83%: 8 green lights on 84%-99%: 10 green lights on

Fully charged, all green lights on, red light off

Nutrition Is The Mission! ™

| _ | Model: | BRv3 |
|---|-----------------------------------|---------------------|
| | Jar Capacity : | 600ml |
| | Jar Material : | AS |
| | Base Material : | ABS |
| | Blade Material : | 304 Stainless Steel |
| | Blending Voltage : | 7.4V |
| | Charging Voltage / Current : | 5V / 1A |
| | Battery Type / Capacity : | 18650 / 2000mAh*2 |
| | Motor Speed : | 18000rpm |
| | Charging Time : | About 3 to 5 hours |
| | Single blend time of Blend mode: | 30 seconds a cycle |
| _ | Maximum blend time of Pulse mode: | 30 seconds |
| | | |

"JUST BOTTLE ROCK IT!!!" ™

Warranty

We offer 12 months warranty on all our products for fault or product quality. Accidental damage or damage as a result of misuse is not covered under this warranty.

Bottlerocketblenders@gmail.com

Anti-slip